

# CONVERTITORE DI RUGGINE- RUST CONVERTER



## Description

CONVERTITORE DI RUGGINE - CONVERTER OF RUST transforms rust into a metallic-organic compound of a black appearance which adheres perfectly to the surface, forming a protective film which can be painted over.

## Composition

Synthetic resins dissolved in water, does not contain solvents.

## Surfaces

CONVERTITORE DI RUGGINE is suitable for the protection of all iron based metalwork both for interiors and exteriors : cast iron, steel, wrought iron, white iron, zinc-plated steel.

Can be used on doors, gates, fencing, guttering, grills, garden furniture, car bodies, domestic appliances and in general, all iron products.

## Preparation of surfaces

Before applying CONVERTITORE DI RUGGINE, clean the rusty areas with a brush and then wash with water, being careful not to remove all of the rust.

## Application

The product is ready to use, apply without diluting it, repeat the operation if there is a lot of rust present; do not soak the brush directly in the bottle and after use, do not put any unused residue liquid back in the bottle.

To ensure it is thoroughly mixed, always shake well before use.

Allow to dry for at least 12/15 hours and then proceed with painting with any kind of paint product.

Do not use the product at temperatures below +5 °C or above +30 °C.

## Consumption

CONVERTITORE DI RUGGINE covers a surface of about 12 / 15 m<sup>2</sup> per litre of product.

## Equipment for application

CONVERTITORE DI RUGGINE is applied by brush in such a way that it soaks well into the rust.

Equipment used for application can be washed in water.

## Packaging and storage

Bottles of lt 0,750

Tins of lt 4

CONVERTITORE DI RUGGINE should be stored in the original containers, well-sealed. It is stable for at least 12 months, providing the room temperature is not below +5°C or above +30°C.

## Health and safety regulations

Rust converter is not a dangerous product.

Do not swallow, keep out of the reach of children, avoid contact with the eyes and do not throw residue into the drainage system.

For further information consult the health and safety sheet.

## Disposal

Dispose of the product according to local health and safety regulations. Empty containers must be recycled.

Data : 27/09/19

The advice and information given above are based on our experience and are of an informative nature and do not bind us to any responsibility. The application of the product takes place without our direct control, the user therefore takes all responsibility for any consequence of use. Our technical assistance team is available for any further information that might be necessary.

Technical data sheet CR/0001

## CONVERTITORE DI RUGGINE- RUST CON- VERTER



---

The advice and information given above are based on our experience and are of an informative nature and do not bind us to any responsibility. The application of the product takes place without our direct control, the user therefore takes all responsibility for any consequence of use. Our technical assistance team is available for any further information that might be necessary.

---